

Edit Smart Server

To edit smart compute resource settings:

1. Go to your Control Panel's **Smart Servers** menu.
2. Click the label of the server you want to edit.
3. Click the **Tools** button and select the **Edit smart server** link. You can edit the label, pricing, CPU and RAM resources for all smart servers. You can also edit the time zone for Windows smart servers.



After you edit the server's time zone, you need to stop and then start up the smart server.

Currently, the time zone is set at the Compute resource side only. Therefore, users need to set the target time zone inside a Windows smart server manually. Setting correct time zone at the Compute resource side helps to keep correct time inside a smart server after starting it if time synchronization is not completed for some reason.

Depending on the OS it is built on, some smart servers can have their CPU and RAM resized without needing to be powered off ("resize without reboot").

4. Click the **Save** button to save your changes.



If the smart server template allows resize without reboot, the resize should be completed automatically: you will be returned to the server details screen and see a message indicating the resize was successful. If the template does not allow this, you will be asked to confirm that the smart server will need rebooting so that the resize can take place.